




Baseline product line

DoubleButton Jeweller

Wireless hold-up device




- 2
GRADE
EN 50131
- PD 6662
2017
- SIA
CP-01
- UL®
LISTED
- IP55




Zero false alarms

- Activation requires pressing both buttons
- Alarm confirmation by pressing both buttons twice using short and long presses in any sequence¹
- Plastic divider prevents accidental activation
- No false alarms when carrying the device in a pocket or a bag




Jeweller communication technology

- Up to 1,300 m of radio communication with a hub
- Encryption for secure data transmission
- Frequency hopping prevents interference and jamming of the radio signal



Effortless maintenance

- Up to 5 years of operation with a pre-installed battery
- No substantial maintenance required



Quick installation and setup

- Remote control and configuration in Ajax apps
- No enclosure disassembly or battery installation required
- Easy device installation on a surface using Holder²
- Option to hang the device on a lace or a keychain

Superior, Fibra, and Baseline product lines are mutually compatible. This opens up numerous possibilities for building systems of any configuration.

Compliance	Compatibility	Communication with a hub	Power supply
EN 50131 (Grade 2) PD 6662:2017 SIA CP-01 UL2610	Hubs Hub Jeweller, Hub Plus Jeweller, Hub 2 (2G) Jeweller, Hub 2 (4G) Jeweller, Hub 2 Plus Jeweller, Hub Hybrid (2G), Hub Hybrid (4G) Range extenders ReX Jeweller, ReX 2 Jeweller	Jeweller communication technology Communication range up to 1,300 m In an open space Radio frequency band 866.0–866.5 MHz 868.0–868.6 MHz 868.7–869.2 MHz 905.0–926.5 MHz 915.85–926.5 MHz 921.0–922.0 MHz Depends on the sales region	Battery life Up to 5 years Battery type 1 × CR2032 Pre-installed

Enclosure Colour black, white Dimensions 47 × 35 × 16 mm Weight 17 g Protection class IP55	Installation Operating temperature range from –10 °C to +40 °C Operating humidity up to 75%	Complete set DoubleButton Jeweller 1 × CR2032 battery (pre-installed) Quick start guide	
---	--	---	--

- 1 — You can also confirm an alarm by pressing two or more DoubleButton devices. In this case, it doesn't matter how the devices were activated, whether with a short or long press.
- 2 — Holder is the bracket for fixing DoubleButton on a surface. Holder is sold separately.



For detailed information, scan the QR code or follow the link:
support.ajax.systems/en/manuals/doublebutton

- support@ajax.systems
- @AjaxSystemsSupport_Bot
- ajax.systems